

eCatcher sets Tap-Win32 IP via NETSH or DHCP command

1. NETSH or DHCP

From version 3.0.1 until version 5.0 then starting again version 5.1, eCatcher uses a NETSH (network shell) command to set the VPN IP address of the Tap-Win32 adapter.

In other versions (prior to 3.0.1 and between 5.0 and 5.1) of eCatcher the IP address of the Tap-Win-32 adapter was attributed using DHCP by default.

The use of netsh is a more direct way to set the IP address than using the DHCP feature on the Tap-Win32 adapter.

But it might happen that on some PC configurations the netsh command fails. If such behavior should happen, eCatcher will display an error message.

2. Error Messages

```
Cannot connect to Talk2MServer:> FATAL:NETSH: command failed
```

or

```
Cannot connect to Talk2MServer:> FATAL>Error:When using --ip-win32 netsh, if you have more than one Tap-Win32 adapter, you must also specify -dev-node"
```


or

```
VPN tunnel error: Cannot assign IP address to TAP-Win32 adapter using NETSH
```

In these cases, to allow the VPN connection, you can change back to the IP address attribution mode using DHCP. To achieve this follow the steps listed hereunder:

1. Close the eCatcher application.
2. Open the "\\Talk2mVpnService\\conf\\" folder of the directory where eCatcher is installed.
By default this should be "C:\\Program Files (x86)\\eCatcher-Talk2M\\Talk2mVpnService\\conf"

3. Open the "Talk2MClient.ovpn" file using notepad.
4. Replace the line "--ip-win32 netsh" with following 2 lines:
 - dhcp-renew
 - dhcp-release
5. Save the file.
6. Launch the eCatcher software.



```
Talk2MClient.ovpn - Notepad
File Edit Format View Help
resolv-retry infinite
nobind
comp-lzo
persist-key
persist-tun
--ip-win32 netsh
dhcp-renew
dhcp-release
verb %VERB%
mute 20
```

Revision

Revision History

Revision Level	Date	Description
1.0	27/04/2011	Creation of document
1.1	27/10/2015	Adding Error message Version of NETSH / DHCP

Document build number: 48

Note concerning the warranty and the rights of ownership:

The information contained in this document is subject to modification without notice. Check <http://wiki.ewon.biz> for the latest documents releases.

The vendor and the authors of this manual are not liable for the errors it may contain, nor for their eventual consequences.

No liability or warranty, explicit or implicit, is made concerning the quality, the accuracy and the correctness of the information contained in this document. In no case the manufacturer's responsibility could be called for direct, indirect, accidental or other damage occurring from any defect of the product or errors coming from this document.

The product names are mentioned in this manual for information purposes only. The trade marks and the product names or marks contained in this document are the property of their respective owners.

This document contains materials protected by the International Copyright Laws. All reproduction rights are reserved. No part of this handbook can be reproduced, transmitted or copied in any way without written consent from the manufacturer and/or the authors of this handbook.

eWON sa, Member of ACT'L Group