



Application User Guide

AUG 067 / Rev. 1.1

How to migrate an eWON from one Talk2M account to another

Learn how to migrate an eWON from one Talk2M account to another, locally or remotely ?



support.ewon.biz



Table of Contents

- 1. Introduction 3**
 - Phase 1: Create the eWON in the new Talk2M account 3
 - Phase 2: Migrate the eWON from the old to the new account: 3
 - Migration flowchart 4
 - New eCatcher 5.x versus old eCatcher 2.1 : 5
 - eWON Scripting: 5
- 2. Phase 1: Create the eWON in the new Talk2M account 6**
 - Step 1: eWON creation process 6
 - Step 2: Get the eWON Activation Key 7
- 3. Phase 2: Migrate the eWON from the old to the new account 8**
 - A) Using a local connection (preferred) 8
 - Step 3: Upgrade the eWON firmware if needed. 8
 - Step 4: Stop the VPN connection. 8
 - Step 5: Launch the Talk2M wizard on the eWON. 9
 - B) Using a remote connection 11
 - Step 3: Upgrade the eWON firmware if needed 11
 - Step 4: Create the remotewizard.txt file 11
 - Step 5: Copy the remotewizard.txt file in your eWON 12
 - Step 6: Launch the Remote Wizard on the eWON 14
- Revision 15**
 - Revision History 15

- Read this important note first -

Migrating an eWON from a Talk2M account to another is easy. In just a few steps, you will be able to access your eWON from your new account.

However, we do recommend taking a few basic precautions to make sure your migration runs as smooth as possible.

If you have local access to your eWON, we strongly recommend to migrate using a point-to-point connection.

If you have to migrate using a remote connection, we recommend doing it at a time when others will not need to access the eWON and when you are unlikely to experience power or communication disturbances. It is safer, though not mandatory, to have a person available on-site during the migration process. The migration uses a special eWON feature named **Remote Wizard**. This feature has nothing to do with the Wizard configuration tool of the eWON website.

1. Introduction

This document describes how to migrate an eWON from one Talk2M account to another. This includes, but is not limited to, the migration from a Talk2M Free to a Free+ account.

In the migration process, there are 2 different phases:

Phase 1: Create the eWON in the new Talk2M account

- Step 1: eWON creation process
- Step 2: Get the new Activation Key

Phase 2: Migrate the eWON from the old to the new account:

A) Using a local Ethernet connection on the eWON (preferred)

- Step 3: Upgrade the eWON firmware if needed
- Step 4: Stop the VPN connection
- Step 5: Launch the Talk2M wizard on the eWON

B) Using a remote connection


- Step 3: Upgrade the eWON firmware if needed
- Step 4: Create the **remotewizard.txt** file needed for the Remote Wizard
- Step 5: Copy the **remotewizard.txt** file into the eWON **/usr** directory
- Step 6: Launch the Remote Wizard on the eWON

- Note -

*Migrating an eWON remotely (through the existing remote connection) requires to use the **Remote Wizard** file. It **cannot** be done using the Talk2M Wizard pages of the eWON.*

Migration flowchart

The following flowchart summarizes the migration process described hereinafter.




New eCatcher 5.x versus old eCatcher 2.1 :

If you are migrating from an old Talk2M Free account you need to use the matching eCatcher 2.1 software (the same one you used to actually create this Talk2M Free account). On the contrary, this old version of eCatcher will not allow you to connect to your new Talk2M Free+ and Talk2M Pro accounts!

Talk2M Free+ accounts can only be created/accessed with eCatcher version 5.x or higher. It can be downloaded here: <https://ewon.biz/support/product/download-zone/all-software>

To perform the migration of an old **Free** account remotely, you will need to use both software versions. You will need to use the eCatcher version 5.x (or higher) to create and manage your eWON in your new **Free+** account and you will need to use the eCatcher version 2.1 to connect to the eWON remotely to launch the **Remote Wizard**.

You can easily identify the 2 different versions:



- Important -

During the installation process of eCatcher version 5.x it can happen that the Tap-Win32 adapter used by the old eCatcher 2.1 version gets deleted. In order to be able to connect using your old Talk2M Free account you then need to add manually the Tap-Win32 adapter.

*To do this, go on the C:\Program Files (x86)\eCatcher\drivers directory and click on the **addtap.bat** command file.*

eWON Scripting:


If you have a script running on your eWON, we strongly recommend to turn the script off during the Talk2M migration phase. Open the **Script Control** window of your eWON and uncheck the **Script starts at eWON Boot option**. Don't forget to turn this option back ON once your Talk2M migration will be completed.

2. Phase 1: Create the eWON in the new Talk2M account


Step 1: eWON creation process

Launch eCatcher V5.x (or higher) and log into your Talk2M account.

On the menu on the left side of the eCatcher interface click on the eWONs button (default view). To add a new eWON on your account, click on the "+" icon in the eWON list section.




The following window opens



- Enter the **eWON name** and description
- Select the applicable **Connection Type**

Click **Next**




- Filling out the **Custom Fields** is also optional

Click **Create**

The Talk2M Connectivity window will open (see next step).

Step 2: Get the eWON Activation Key

- In the **Configure via Activation Key** area click **Copy to Clipboard** to copy the **Activation Key** in your clipboard.



3. Phase 2: Migrate the eWON from the old to the new account

If you have local access to your eWON, we strongly recommend to migrate with a local connection using the eWON LAN port.

If you do not have local access to your eWON then you can use the **Remote Wizard** feature of the eWON. This feature allows you to launch a wizard on the eWON without using the web interface. Furthermore, if the wizard fails, the eWON will re-apply the old configuration so you can continue to connect to your eWON remotely.

A) Using a local connection (preferred)


Step 3: Upgrade the eWON firmware if needed.

- If your eWON firmware version is < 6.2s0 you need to upgrade first.
- The easiest way to upgrade the firmware is to connect to the eWON LAN side and to use eBuddy.
- Detailed info can be found here: <https://ewon.biz/support/product/download-firmware/firmware-2>


Step 4: Stop the VPN connection.

Before launching the Talk2M wizard, you need to stop the current VPN connection.

Follow the menu path **Configuration > System Setup > Communication > Networking Config > VPN Connection** and select the **Disable VPN** option as indicated in the picture below:




On recent firmware the path has slightly changed:




Step 5: Launch the Talk2M wizard on the eWON.

To open the wizard window, click on **Configuration** in the toolbar and then on the **wizard icon** (1). The wizard window opens:



Click on **Talk2M** (2).

The following window is displayed



Click **Next**

Paste the **Activation Key** you still have on your clipboard from the previous step.



Click **Next** until the wizard completes (tests should be successful).

Your eWON should now be connected to your new Talk2M account.

Open eCatcher to check if the eWON can be reached through the new Talk2M account.

B) Using a remote connection

Step 3: Upgrade the eWON firmware if needed

- If your eWON firmware version is < 6.2s0 you need to upgrade first.
- The easiest way to upgrade the firmware is to connect to the eWON LAN side and to use eBuddy.
- Detailed info can be found here: <https://ewon.biz/support/product/download-firmware/firmware-2>

Step 4: Create the remotewizard.txt file

To migrate the eWON from the old to the new account, you will use the remote wizard feature of the eWON. Therefore, you first need to create the file needed for the Remote Wizard.

Contents of **remotewizard.txt** file

```
:  
:main  
wizardname:t2mCnx  
:  
:com  
T2mAccSrvAddr:talk2m_pro  
:  
:wizard  
T2mActivationKey:7aaf9d27c082039e49c806df78589910
```

- Warning -

*The correct syntax needs a carriage return (invisible) after the **Activation Key**. If you copy/paste the syntax above, this carriage return may not be included. Please verify and add it manually after pasting.*

To create this file proceed as follows:


1. Open the notepad application on your PC
2. Copy/paste the lines displayed above
3. Replace the **Activation Key** (displayed in red in our example) with the one you gathered in the previous step. Add a carriage return (hit the Enter key) manually at the end!
4. Save the file under the following name on your PC: remotewizard.txt

Step 5: Copy the remotewizard.txt file in your eWON


Connect to your eWON using your old account (eCatcher 2.1 if it was a Free account) and open an FTP session on your eWON.

If you do not have an FTP client software on your PC, then you can use the Windows Explorer instead:

- Open Windows Explorer (**NOT** Internet Explorer) on your PC
- enter **ftp://** followed by the **IP address of your eWON**.
- As IP address of the eWON you can use either its local LAN IP address or its VPN IP address.
- The **Login** window appears




- Enter the eWON user name and password.
- Once logged in, the FTP directory of the eWON will be displayed.



- Open the **usr** directory and copy the remotewizard.txt file into it.


You can use the drag and drop feature of your PC to copy the remotewizard.txt into the FTP folder



Close your FTP connection (just close the window if you are using Windows Explorer as the FTP client).

Step 6: Launch the Remote Wizard on the eWON

Follow the menu path **Configuration > SystemSetup > Storage > Reboot**



Select the **Enable Remote Wizard** option in the **Special Operation** field and click on the **REBOOT** button. The eWON will reboot and launch the remotewizard.txt file.

The eWON is now disconnected from its old Talk2M account. Hence it is displayed as **Offline** on the old account. A few minutes later your eWON appears as **Online** on your new account.

- Note -

a) To be able to connect to the eWON in your new account, you need first to close the eCatcher session corresponding to the old account (for a Free account, this is an eCatcher 2.1 session). Otherwise the VPN connection will not be possible.

b) If, for any reason, the remote Talk2M wizard would have failed without you noticing, the eWON would restart using its old VPN settings. Therefore, the eWON will not be online in your new account, but should still be accessible through your old account.



Revision

Revision History

Revision Level	Date	Description
1.0	02/05/2014	Document creation
1.1	23/09/2016	Document revision

Document build number: 3

Note concerning the warranty and the rights of ownership:

The information contained in this document is subject to modification without notice. Check <https://ewon.biz/support> for the latest documents releases.

The vendor and the authors of this manual are not liable for the errors it may contain, nor for their eventual consequences.

No liability or warranty, explicit or implicit, is made concerning the quality, the accuracy and the correctness of the information contained in this document. In no case can the manufacturer's responsibility be implied for direct, indirect, accidental or other damage occurring from any defect of the product or mistakes coming from this document.

The product names are mentioned in this manual for information purposes only. The trade marks and the product names or marks contained in this document are the property of their respective owners.

This document contains materials protected by the International Copyright Laws. All reproduction rights are reserved. No part of this handbook can be reproduced, transmitted or copied in any way without written consent from the manufacturer and/or the authors of this handbook.

eWON sa